



Each switch hole is $\frac{1}{2}$ L by $\frac{1}{4}$ H. Each switch hole is separated by $1 \frac{5}{8}$ edge to edge. Each switch hole top edge to top of dark green area is $\frac{1}{8}$

Center of each control hole is $2 \frac{1}{8}$ to Center of the next hole to the left. Each control hole is $\frac{3}{8}$ diameter

The center of right hole down $\frac{7}{8}$ to bottom of dark green area and the center of right hole, $1 \frac{3}{4}$ to right edge of dark green area

PHONES hole is $\frac{7}{16}$ from center of hole to left dark green edge and $\frac{7}{16}$ center of hole down to bottom dark green area edge. PHONES hole diameter is $\frac{3}{8}$.

Heathkit HR10 front panel dimensions
All dimensions are in "inches"

$\frac{1}{4}$ "

$2 \frac{1}{2}$

$2 \frac{9}{16}$

$\frac{1}{8}$

$3 \frac{1}{8}$

$9 \frac{7}{8}$

2 inches

$\frac{7}{16}$

$\frac{1}{4}$

$3 \frac{1}{4}$